

## Installing Archnet Printers on Mac OS X Yosemite

1. Open a web browser and type in the following URL: `http://localhost:631`
2. If you encounter an error message that the interface is currently disabled open the Terminal app in `/Applications/Utilities` and run `"cupsctl WebInterface=yes"` to enable it.
3. Click on the 'Administration' tab at the top of the CUPS page. If prompted to login, use your laptop administrator account.
4. Select 'Add Printer'.
5. At the bottom of the page, under the 'Other Network Printers' option select 'Windows printer via spoolss' and click 'Continue'.
6. In the Connection field, enter **`smb://netid;username:password@128.95.103.39/PrinterName`** and edit anything in italics. For *username* use your NetID username, and *password* is your NetID password. PrinterName should be replaced by the Printer Share Name as listed in the table below. Click 'Continue' when done editing.
7. In the 'Name' field, type in the name you would like to use for this printer. Spaces are not allowed in this field. (Ex:Archnet\_BW) The 'Description' and 'Location' fields can be left blank or filled in as desired.
8. Select 'HP' as the printer manufacturer and press 'Continue'.
9. Select the model of the printer as indicated by the table on the next page and press 'Add Printer'. If you do not see the correct model listed, please download and install the HP printer drivers available at [support.apple.com/kb/dl907](http://support.apple.com/kb/dl907).
10. Select any Default Options for the printer as listed in the table below.

<b><i>Printer Share Name</i></b>	<b><i>Printer Driver</i></b>	<b><i>Additional Options</i></b>
BW_Laserjet	HP Laserjet 5200	Tray 3 & Duplex Unit
Color_Laserjet_M750	HP Color Laserjet Enterprise M750	Tray 3 & Duplex Unit
FAST_36_WIDE	HP DesignJet T7100ps	N/A
MATTE_42_WIDE	HP DesignJet T7100ps	N/A
GLOSSY_42_WIDE	HP DesignJet T1120ps 44in	N/A